

# การตั้งค่า Yeastar S50

Settings > PBX > Trunk > Basic

### Edit VoIP Register Trunk ( cat2callplus )

Basic | Codec | Advanced | DOD | Adapt Caller ID

Trunk Name: cat2callplus Trunk Status: Enabled

Protocol: SIP

Trunk Type: Register Trunk

Voicemail Template: General

General Transport: UDP

Recording Hostname/IP: catnextgen.com : 0

System Domain: catnextgen.com

Username: +6621079021 Password: \*\*\*\*\*

Authentication Name: 6621079021@catnextgen From User: +6621079021

Caller ID Number: +6621079021 Caller ID Name:

Enable Outbound Proxy

Outbound Proxy Server: 202.129.61.102 5060

Save Cancel

พื้มพ์ 66 ตามด้วยเบอร์โทร และ @catnextgen.com  
เช่น 6621079021@catnextgen.com

พื้มพ์ +66 ตามด้วยเบอร์โทร เช่น +6621079021

PBX Monitor

Extensions

PBX > Call Control > Inbound Route

### Edit Inbound Route ( CAT )

Name: CAT

DID Pattern: +6621079021

Caller ID Pattern:

Member Trunks:

Available: FXO3 (FXO), FXO4 (FXO), AIS3G (UMTS), True3G (UMTS)

Selected: cat2callplus (SIP-Register)

Save Cancel

**PBX Monitor**

Extensions Settings

Trunks

Concurrent Call

Call Control

Call Features

Voice Prompts

General

Recording

Emergency Number

System

Event Center

1/1

**PBX > Call Control > Inbound Route**

**Edit Outbound Routes ( CAT2Call )**

Name: CAT2Call

Dial Patterns: +

Patterns	Strip	Prepend	Edit	Delete
0.				

Member Trunks:

Available	Selected
FXO3 (FXO)	cat2callplus (SIP-Register)
FXO4 (FXO)	
AIS3G (UMTS)	
True3G (UMTS)	

Save Cancel